Anritsu envision : ensure

Analog Wireless (FM/ΦM/AM) Test Solution

- Analog Measurement Software MX269018A -

Signal Analyzer MS2830A / MS2840A

Version 15.00

Signal Analyzer MS2830A/MS2840A

The Analog Measurement Software **MX269018A** for the Signal Analyzer **MS2830A/MS2840A** measures the TRx performance of analog wireless equipment (FM/ΦM/AM). Combining options such as the analog signal generator, audio analyzer, etc., according to the measurement items supports fast, high–accuracy measurements for development, production and maintenance of analog wireless equipment.

✓: Supported; Blank: Not supported

Main Option Function Application MS2840A MS2830A Multi-function middle-class spectrum Middle-class spectrum analyzer/signal analyzer with excellent close-in phase analyzer/signal analyzer with excellent cost-performance noise performance exceeding top-class Options for improved phase noise instruments performance for measuring close-in Substitute for aging high-end spectrum spurious and adjacent channel leakage analyzers power (ACP) of narrowband wireless • Options for digital wireless measurements equipment and both analog/digital measurements • Options for digital wireless measurements and both analog/digital measurements 3.6 GHz/6 GHz 13.5 GHz 3.6 GHz/6 GHz 26.5 GHz/44.5 GHz Model Model Model Model **Analog Modulation Tx Tests** \checkmark \checkmark Analysis (FM/ΦM/AM) **Analog Signal Generator** \checkmark **Rx Tests** $(FM/\Phi M/AM)$ \checkmark \checkmark **Audio Analyzer TRx Tests**

Section 1

MS2830A

- Set-up
- Recommended Configuration
- Function and necessary composition
- Function Comparison between Legacy Model
- I/O Connectors
- Example of Connection Between DUT and Audio Analyzer
- Interface Setting Example of Audio Analyzer
- Spectrum Analyzer Function Excellent SSB phase noise performance

MS2840A

- Set-up
- Recommended Configuration
- Function and necessary composition
- I/O Connectors
- Spectrum Analyzer Function
 Excellent SSB phase noise performance

MS2830A Set-up



MS2830A (3.6 GHz/6 GHz models)

Installing the Analog Signal Generator and Audio Analyzer options supports all-in-one measurement of main TRx characteristics (FM/ΦM/AM) of analog wireless equipment.

MS2830A (13.5 GHz model)

Installing the Audio Analyzer option supports all-in-one measurement of main Tx characteristics (FM/ΦM/AM) of analog wireless equipment. The Analog Signal Generator option cannot be installed.

Analog Wireless Measurement Recommended Configuration (MS2830A)

At New Signal Analyzer **MS2830A** Purchase **Required Options**

*The latter half of this document provides ordering information including retrofit options for the MS2830A and how to select the signal generator.

No.	Model	Name	Note	
	MS2830A-040	3.6 GHz Signal Analyzer	Select any one of the following.	
1	MS2830A-041	6 GHz Signal Analyzer	MS2830A-040: 9 kHz to 3.6 GHz MS2830A-041: 9 kHz to 6 GHz MS2830A-043: 9 kHz to 13.5 GHz	
	MS2830A-043	13.5 GHz Signal Analyzer		
2	MS2830A-066	Low Phase Noise Performance	Improved phase noise performance: The MS2830A with MS2830A-066 option measures close-in spurious and adjacent channel leakage power (ACP) with excellent SSB phase noise performance.	
3	MX269018A	Analog Measurement Software	Frequency setting range: At FM/ΦM/AM measurement: 100 kHz to the upper limit of the main unit At Wide Band FM measurement: 10 MHz to the upper limit of the main unit	
4	A0086C	USB Audio	Outputs demodulated audio for Tx test	

Recommended Options $\langle \checkmark \checkmark$: Required, \checkmark : Recommended, Empty; Not required>

No.	Model	Name	Tx Test Only	Tx/Rx Test	Note
5	MS2830A-018	Audio Analyzer	$\checkmark\checkmark$	$\checkmark\checkmark$	AF Signal I/O function with built-in white-noise generation (ITU-T Recommendation G.227) and PTT Control functions
6	MS2830A-088	3.6 GHz Analog Signal Generator		$\checkmark\checkmark$	Frequency setting range (FM/ΦM/AM): 100 kHz to 3000 MHz Cannot be installed with MS2830A-043
7	MS2830A-002	High Stability Reference Oscillator	\checkmark	\checkmark	Aging rate: $\pm 1 \ge 10^{-7}$ /year Start-up characteristics: $\pm 5 \ge 10^{-8}$ (5 minutes after power- on)
8	MS2830A-052	Internal Signal Generator Control Function		\checkmark	Equivalent functions to tracking generator for measuring transmission characteristics (frequency characteristics) of filters, amplifiers, etc.

Function and necessary composition (MS2830A)

Ana	Analog measurement software function [MS2830A] ^{*1}					Requires Options
	-		FM	ΦM	AM	1
Tx Tests	RF Measure	Carrier Frequency and Carrier Frequency Error		~	~	1, 2, 3, 4 is mandatory
		Transmit Power	~	~	~	1. Signal Analyzer (MS2830A-
		Modulation measurement Deviation(FM), Radian(ϕ M), Depth(AM)	~	~	~	2. Low Phase Noise Performance
		Result of analyzed DCS Code DCS Code	~			(MS2830A-066)
	AF Measure (Demodulation)	Demodulation Frequency AF Frequency	~	~	~	(MX269018A)
		Effective Value for Level at Demodulation Frequency Level	~	~	~	4. USB Audio (A0086C) 5. commercial speaker
		Distortion Ratio of Demodulation Frequency Distortion Distortion, SINAD, THD	~	~	~	
		Time vs. Level, Frequency vs. Level Graph Result	~	~	~	*: MS2830A-043 cannot be installed MS2830A-066 and 7. Analog Signal
		Demodulate Input RF Signals from wireless equipment and Output Voice from USB connector *2		~	~	Generator simultaneously.
		Demodulate Input RF Signals from wireless equipment and Output Sound from Internal speaker, Headphone jack and Demodulation Output Connector				1 + 2 + 3 + 4
	AF Output AF tone, DCS, White Noise (ITU-T Recommendation G.227), DTMF (Audio Generator Function)		~	~	~	+ 6 Audio Analyzer (MS2830A-018)
	PTT (Push To Talk) co	ntrol	✓	✓	✓	1
Rx	RF Output	Modulation Signal Output (FM, ΦΜ, AM)	✓	✓	✓	1 + 2 + 3 + 4
Tests		Internal Modulation Signal Source(AF tone)	 ✓ 	 ✓ 	✓	1 7 Applea Signal Constator
		Internal Modulation Signal Source(DCS)	 ✓ 			+ 7 Analog Signal Generator
	AF Measure (Audio Analyzer	Frequency AF Frequency	~	~	~	
	Function)	Effective Value for Level Level	~	~	~	1 + 2 + 3 + 4
		Distortion Ratio SINAD, THD, THD+N	~	~	✓	+ 6 Audio Analyzer (MS2830A-018)
		Graph(Time vs. Level, Frequency vs. Level) Graph Result	~	~	✓	
	PTT (Push To Talk) of	control	 ✓ 	 ✓ 	✓	

*1: Spurious can also be measured using the standard spectrum analyzer measurement function. *2: Voice can be monitored by connecting a commercial loudspeaker using the A0086A, A0086B or A0086C USB Audio. *3: The Wide Band FM measurement mode is not supported.

Function Comparison between Legacy Model MS555 Series and MT2605 Series Radio Communication Analyzer

Items (Using FM Radio)		MS555 series	MT2605 series	MS2830A Audio Analyzer (MS2830A-018) Low Phase Noise Function (MS2830A-066) Analog Signal Generator (MS2830A-088) Analog Measurement Software (MX269018A)		
		Tx Power	✓	✓	√	
ר	Tx	Tx Frequency	✓	✓	\checkmark	
	Test	FM Deviation	✓	✓	✓	COUCHE CALL CARENT A
		Microphone input sensitivity	✓	✓	✓	
		Modulation frequency characteristics	✓	✓	✓	6-6. 6. 0 Martin
		Distortion	✓	✓	✓	MS555
Toct		S/N	✓	✓	✓	Series
Itoms		Tone frequency	✓	✓	✓	
Items		SINAD	✓	✓	✓	
	Rx	Bandwidth	✓	✓	√ *1	
	Test	AF Level	✓	✓	✓	Tarty or American and Day measure
		Demodulation frequency characteristics	✓	✓	✓	(C 5 e 5 e 5)
		Distortion	\checkmark	✓	\checkmark	
		S/N	\checkmark	\checkmark	\checkmark	• ··• • at at a a a a
		Squelch sensitivity	\checkmark	\checkmark	\checkmark	MT2605
		Spectrum Analyzer		√ *3	\checkmark	Series
		Frequency Counter	\checkmark	✓	\checkmark	
		Power Meter	\checkmark	\checkmark	√ *2	
		FM Linear Detector	\checkmark	\checkmark	\checkmark	
Fui	nction	AF Level Meter	\checkmark	✓	\checkmark	
		AF Oscillator	\checkmark	\checkmark	\checkmark	*1 [.] Requires manual
		RF Signal Generator	\checkmark	\checkmark	✓	calculation
		Monitor demodulated audio signal	✓	\checkmark	\checkmark	*2: Requires ontional LISB
		AF Oscillator for tone squelch	✓	✓	✓	Power Sensor
		White noise (ITU-T Recommendation G.227)		\checkmark	\checkmark	3: Low Phase Noise

Function is not available.

MS2830A I/O Connectors (Analog Signal Generator/Audio Analyzer)



	No.	Name		Connector	Note	
	1	SG Output		N-J	100 kHz to 3000 MHz (FM/ΦM/AM)	
Front	2	RF Input		N-J	9 kHz to 3.6 GHz, 6 GHz or 13.5 GHz* Frequency setting range (At FM/ΦM/AM measurement): 100 kHz to the upper limit of the main unit	
	3	AF Input	Unbal 100 kΩ	BNC-J	Unbalanced, 100 k Ω (AC coupling, nominal)	
	4	AF Input Bal 200 kΩ		1/4 inch phone jack (3 poles, Φ6.3 mm)	Balanced, 200 k Ω (AC coupling, nominal)	
	5	Audio Function		D-sub15pin (jack)	Open collector x1 (5V,100 mA max.), TTL Output x2, TTL Input x2	
	6	PTT (-)		Banana jack (Φ4.0 mm)	PTT control () (1) 20 / may E00 mA may	
Back	7	PTT (+)		Banana jack (Ф4.0 mm)	PTT control (–) (+), SOV max., SOU ma max.	
Dack	8	AF Output	Unbal 50 Ω/600 Ω	BNC-J	Unbalanced, 50/600 Ω (AC coupling, nominal)	
	9	AF Output	Bal 100 Ω/600 Ω	1/4 inch phone jack (3-pole, Ф6.3 mm)	Balanced, 100/600 Ω (AC coupling, nominal)	
	10	Demod Out 600 Ω		BNC-J	Demodulation Output (FM only) -10 dBm \pm 0.2 dB (Frequency Deviation = 3.5 kHz, 600 Ω)	
	11	0		3.5 mm phone jack (2-pole)	Demodulation Output (FM only, for headphones, monaural)	
	*: 13.5 GHz model (MS2830A-043) does not have built-in signal generator.					

AF Input connector (Balanced) AF Output connector (Balanced)

1/4 inch phone jack (3 poles, Φ6.3 mm)



AF Output







< 1/4 Inch Phone Plug >

General Input/Output (Audio Function) connector

D-Sub 15



Pin Number	Signal Name
1	GND
2	GND
3	GND
4	RSV (Reserved)
5	RSV (Reserved)
6	GND
7	GND
8	GND

<	connector	pin	assignment >	

Pin Number	Signal Name		
9	Open collector		
10	TTL Output 1		
11	TTL Output 2		
12	Non Connection		
13	TTL Input 1		
14	TTL Input 2		
15	Non Connection		

Ancitsu envision : ensure

Example of Connection Between DUT and Audio Analyzer (1/2)

This figure shows an example of connection between the DUT and the Audio Analyzer MS2830A-018/118. Either "unbalanced connector" or "balanced connector" can be used for AF input-output connector according to the DUT.



*1: PTT terminal shows polarity for identifying terminals. It doesn't have polarity for a circuit.

PTT terminal has a built-in overcurrent protection circuit. If the protection circuit operates, turn Off the MS2830A and turn it On again.

*2: R1: Termination corresponding to audio output impedance of the DUT.

MS2830A

This figure shows an example of connection between the DUT and the MS2830A-018/118 Audio Analyzer.



Interface Setting Example (Audio Analyzer) (1/4)



This shows a setting example for the Audio Generator Function interface. Set Output Type/Output Impedance at the Tx test.

TX Mode

2016/02/18 19:00:20

Waveform

Tones

Output Tone1

Tone1 Freq

1.000 0kHz

Tone1 Level

1.00mVrms

Output Tone2

Tone2 Freq

67.0Hz

Tone2 Level

1.00mVrms

Tone3

1 of 2

On

Off

Off

On

Analog Modulation

Audio Generator Setting





Audio Generator Function Settings

Output Type	Balanced, Unbalanced
Output Impedance	Balanced: 100Ω, 600Ω Unbalanced: 50Ω, 600Ω
Output Impedance Reference	Sets the impedance reference used for converting power to dBm

When displaying the AF Output output level in power units (conversion), set the AF Output Unit to dBm (or W) and set the input impedance of the DUT side at Output Impedance Reference.

Although the AF Output output level can be displayed in voltage units, in this case it is not necessary to set the Output Impedance Reference (Open Circuit Voltage). The relationship between the power and voltage settings is described in the latter half of this reference (Audio Output Settings) and in the operation manual.

Relationship between Output Level Units and Output Level Display

From MS2830A firmware Package Version 7.03.00 * (all units shipped from March 26, 2015), the relationship between the output units setting and output level display is as follows.

When output units set to dBm	"Termination Power" is displayed. The power consumed by the termination resistance (0 dBm = 1 mW) is displayed. *Up to Package Version 7.02.00, the actual output level was 6 dB lower than the display.
When output units set to mV or V	"Open Circuit Voltage" is displayed.



*: <Firmware Confirmation Method>

Confirm the MS2830A firmware using the following operation. Press [System Config] \rightarrow [F5] System Information \rightarrow [F2] Software Version View, and check the Package Version displayed at the top right of the screen.

Interface Setting Example (Audio Analyzer) (3/4)

Supplementary Explanation: Output level of Audio Generator function

The output level of the Audio Generator can be set to either voltage or power (dBm). The voltage value and power value are converted to each other using the following formula.

When the output level is set as power (dBm) using this Audio Generator function, input the impedance of the DUT connected to the Audio Generator as the reference impedance (Output Impedance Reference (Rr)).

MS2830A Setting Output Impedance (Rs) Customer Usage Status 100Ω 600Ω Power (dBm)*2 Power (dBm)*2 100Ω Termination Open Circuit Voltage/2 (V rms)*1 Open Circuit Voltage × 1/7 (V rms)*1 Power (dBm)*3 Power (dBm)*3 600Ω Termination Open Circuit Voltage \times 6/7 (V rms)^{*1} Open Circuit Voltage/2 (V rms)*1 **High Impedance** Open Circuit Voltage (V rms)*1 Open Circuit Voltage (V rms)*1 (≥100 kΩ)

Actual Output Level

*1: The voltage setting value and display setting value are shown as Open Circuit Voltage irrespective of the Output Impedance (Rs) and Output Impedance Reference (Rr) values.

*2: When Output Impedance Reference (Rr) set to 100 Ω

*3: When Output Impedance Reference (Rr) set to 600 Ω

Formula $dBm = 10 \times log_{10} \left(1000 \times Rr \times \left(\frac{V_{rms}}{Rs + Rr} \right)^2 \right)$

Interface Setting Example (Audio Analyzer) (4/4)

MS2830A





MS2840A (3.6 GHz/6 GHz models)

Installing the Analog Signal Generator option supports all-in-one measurement of TRx characteristics (FM/ΦM/AM) of analog wireless equipment. The Audio Analyzer option cannot be installed.

MS2840A (26.5 GHz/44.5 GHz models)

These models can measure the Tx characteristics (FM/ΦM/AM) of analog wireless equipment. The Analog Signal Generator and Audio Analyzer options cannot be installed.

Analog Wireless Measurement Recommended Configuration (MS2840A)

At New Signal Analyzer MS2840A Purchase

*The latter half of this document provides ordering information including retrofit options for the MS2840A and how to select the signal generator.

With 3.6 GHz Signal Analyzer (MS2840A-040) or 6 GHz Signal Analyzer (MS2840A-041)

Required Options

No.	Model	Name	Note
1	MS2840A-040	3.6 GHz Signal Analyzer	Select any one of the following. Frequency range:
	MS2840A-041	6 GHz Signal Analyzer	MS2830A-040: 9 kHz to 3.6 GHz MS2830A-041: 9 kHz to 6 GHz
2	MX269018A	Analog Measurement Software	Frequency setting range: At FM/ΦM/AM measurement: 100 kHz to the upper limit of the main unit At Wide Band FM measurement: 10 MHz to the upper limit of the main unit
3	A0086C	USB Audio	Outputs demodulated audio for Tx test

• Low Phase Noise Performance MS2840A-066 not required

■ Recommended Options < ✓ ✓: Required, ✓ : Recommended, Empty; Not required>

No.	Model	Name	Tx Test Only	Tx/Rx Test	Note
4	MS2840A-088	3.6 GHz Analog Signal Generator		$\checkmark\checkmark$	Frequency setting range (FM/ΦM/AM): 100 kHz to 3 GHz Cannot be installed with MS2830A-043
5	MS2840A-066	Low Phase Noise Performance	\checkmark	~	Improves phase noise performance. This option greatly improves SSB phase noise performance.
6	MS2840A-002	High Stability Reference Oscillator	~	~	Aging rate: $\pm 1 \times 10^{-7}$ /year Start-up characteristics: $\pm 5 \times 10^{-8}$ (5 minutes after power- on)

• No built-in audio analyzer options

Analog Wireless Measurement Recommended Configuration (MS2840A)

At New Signal Analyzer MS2840A Purchase

*The latter half of this document provides ordering information including retrofit options for the MS2840A and how to select the signal generator.

With 26.5 GHz Signal Analyzer (MS2840A-044) or 44.5 GHz Signal Analyzer (MS2840A-046)

Required Options

No	Model	Name	Note
110.	woder	Nume	
	MS2840A-044	26.5 GHz Signal Analyzer	Select any one of the following.
1			Frequency range:
	MS2840A-046	44.5 GHz Signal Analyzer	MS2830A-040: 9 kHz to 26.5 GHz
			MS2830A-041: 9 kHz to 44.5 GHz
			Frequency setting range:
2	MX269018A	Analog Measurement Software	At FM/ФM/AM measurement: 100 kHz to to the upper limit of the main unit
			At Wide Band FM measurement: 10 MHz to to the upper limit of the main unit
3	A0086C	USB Audio	Outputs demodulated audio for Tx test

• Supports Tx tests only

• No built-in analog signal generator, audio analyzer or low phase noise performance options

• MS2830A-044/046 supports same functions as High Stability Reference Oscillator option (MS2840A-002).

Function and necessary composition (MS2840A)

Analog measurement software function [MS2840A] ^{*1}			Modulation method of target signal		thod of	Requires Options
			FM	ΦM	AM	
Tx Tests	RF Measure	Carrier Frequency and Carrier Frequency Error <u>RF Frequency</u>	~	~	~	
		Transmit Power	~	~	~	*
		Modulation measurement Deviation(FM), Radian(Φ M), Denth(AM)	~	~	~	1, 2, 3 is mandatory
		Result of analyzed DCS Code	~			1. Signal Analyzer (MS2840A-
	AF Measure (Demodulation)	Demodulation Frequency	~	~	~	2. Analog Measurement Software
		Effective Value for Level at Demodulation Frequency	~	~	~	(MX269018A) 3. USB Audio (A0086C)
		Distortion Ratio of Demodulation Frequency Distortion Distortion, SINAD, THD	~	~	~	4. commercial speaker
		Time vs. Level, Frequency vs. Level Graph Result	~	~	~	
		Demodulate Input RF Signals from wireless equipment and Output Voice from USB connector *2	√*3	~	~	*
		Demodulate Input RF Signals from wireless equipment and Output Sound from Internal speaker, Headphone jack and Demodulation Output Connector				
	AF Output AF tone, DCS, White Noise (ITU-T Recommendation G.227), DTMF (Audio Generator Eurction)					Not supported by MS2840A
	PTT (Push To Talk) control		 ✓ 	✓	✓	
Rx	RF Output	Modulation Signal Output (FM, ΦΜ, AM)	✓	✓	✓	Not supported by MS2840A-044/046
Tests		Internal Modulation Signal Source(AF tone)	✓	✓	✓	1 + 2 + 3
		Internal Modulation Signal Source(DCS)	~			+ 5. Analog Signal Generator
	AF Measure	Frequency				
	(Audio Analyzer	AF Frequency				
	Function)	Effective Value for Level				
		Level				
		Distortion Ratio SINAD, THD, THD+N				Not supported by MS2840A
		Graph(Time vs. Level, Frequency vs. Level) Graph Result				
	PTT (Push To Talk) c	control				

*1: Spurious can also be measured using the standard spectrum analyzer measurement function.

*2: Voice can be monitored by connecting a commercial loudspeaker using the A0086A, A0086B or A0086C USB Audio.

*2: Voice ca *3: The Wid

*3: The Wide Band FM measurement mode is not supported.

MS2840A I/O Connectors

MS2840A-040/041 (3.6GHz/6GHz models) with optional Analog Signal Generator installed



MS2840A-044/046 (26.5GHz/44.5GHz models)



No.	Name	Connector	Note
1	RF Input	N-J (26.5GHz model) K-J (44.5GHz model)	9 kHz to 26.5 or 44.5 GHz Frequency setting range (At FM/ΦM/AM measurement): 100 kHz to the upper limit of the main unit

MS2840A

MS2830A/MS2840A Spectrum Analyzer Function Excellent SSB phase noise performance

The MS2830A with installed Low Phase Noise Performance MS2830A-066 option and the MS2840A with standard functions both have excellent SSB phase noise performance for measuring close-in spurious and adjacent channel leakage power (ACP), etc., of narrowband wireless equipment with extremely severe measurement standards.



The MS2840A with installed Low Phase Noise Performance MS2840A-066 option has excellent SSB phase noise performance. In addition to true evaluation of close-in spurious of wireless equipment, it also supports phase noise evaluation of signal sources in wireless equipment.



*: Value measured at design but not guaranteed specification

Section 2



Rx Test

- Measurement System Images
- Measurement Items, Filter Settings
- Analog Signal Generator Settings
- Rx Mode Screen
- Internal Modulation Signal Source
- Useful Meter Displays
- Audio Signal Graph Displays

MX269018A Measurement System Images <Tx Test>



Input AF from Audio Generator to wireless equipment and measure Tx characteristics of RF signals output from wireless equipment.

Built-in Option	Setup	Features and Functions
Analog Measurement Software + Audio Analyzer	MS2830A AF Output FT x test AF Input PTT Control The audio analyzer cannot be installed in the MS2840A.	 Supports Tx tests of FM/ΦM/AM analog radio equipment using all- in-one MS2830A with audio generator function Displays AF signal output settings, RF Tx measurement results and demodulation results (tables/graphs) on one screen In addition to AF tones (3 waveforms max.) also outputs White noise (ITU-T Recommendation G.227) and DTMF Convenient meter displays for adjusting frequency deviation at FM Tx Supports FM deviation measurements up to 1 MHz Supports various settings including HPF, LPF, Weighting Filter and De-emphasis at demodulation measurement DCS Code analysis displays (FM only) PTT (Push To Talk) control
Analog Measurement Software only	MS2830A MS2840 MS284	 Supports Tx tests of FM/ΦM/AM analog radio equipment RF Tx measurement results and demodulation results (table/graphs) confirmed on one screen Convenient meter displays for adjusting frequency deviation at FM Tx Supports FM deviation measurements up to 1 MHz Supports various settings including HPF, LPF, Weighting Filter and De-emphasis at demodulation measurement DCS Code analysis displays (FM only)

MX269018A Measurement System Images <Rx Test>



Output RF signals for confirming operation and Rx Sensitivity tests from analog signal generator to radio equipment. Measure AF output from radio equipment with external Audio Analyzer for Rx Sensitivity tests.



Demodulated Audio Output

MX269018A Measurement System Images < Demodulation Voice Output>

Monitor demodulated audio signals using USB audio, or internal speaker/headphone jack/demodulation output connector. USB audio requires separately sold speaker or headphone.



<Tx Test> MX269018A Measurement Items · Filter Settings



<Tx Test> Settings

Display Item	Outline
Result (Tx Measure)	RF Signal analysis results
RF Frequency	Carrier Frequency and Carrier Frequency Error
RF Power	RF Power
Deviation	Frequency Deviation (FM)
Radian	Phase Deviation (ΦM)
Depth	Modulation (AM)
DCS Code	DCS Code analysis results (FM)
AF Measure	Demodulated signal analysis results
AF Frequency	Demodulated frequency
Level	Demodulated signal rms level
Distortion, SINAD, THD	Demodulated frequency distortion
Graph Results	Time vs Level and Frequency vs Level for demodulated frequency

<Tx Test> Filter Settings (for demodulated signal analysis)

Low Pass Filter	Off, 300 Hz, 3, 15, 20 kHz
High Pass Filter	Off, <1*, <20*, 50, 300, 400 Hz, 30 kHz *FM only
Weighting Filter	Off, CCITT, C-Message, CCIR 468, CCIR-ARM, A-Weighting
De-emphasis	Off, 25 μs, 50 μs, 75 μs, 500 μs, 750 μs

<Tx Test> Audio Output Settings (1/2)



<Tx Tests> Audio Analyzer MS2830A-018/118 Settings (Audio Generator Function)

The following settings are supported when the Audio Analyzer MS2830A-018 (or 118) is installed.

<The Sub Supply/Audio Revision 2^{*1} specifications are presented below (shipped March 26, 2015)>

	AF Tone	Simultaneous output of up to 3 waveforms at any frequency Frequency: 10.0 to 50000.0 Hz (Guarantee Range: 20.0 to 25000.0 Hz) Level: [Output unit: mV rms, V rms, dBm] At 600 Ω termination when output impedance and output impedance reference set to 600 Ω Balanced: off, -63 dBm (equivalent to 0.5 mV rms) to +18 dBm (equivalent to 6.2 V rms) Unbalanced: off, -63 dBm (equivalent to 0.5m V rms) to +12 dBm (equivalent to 3.1 V rms)				
Output	DCS	DCS Code: 000 to 777 (octal, 3 digit) DCS Polarity: Normal (non-inverted polarity output), Inverted (inverted polarity output) Level: [Output unit: mV p, V p] At 600 Ω termination when output impedance set to 600 Ω Balanced: off, 0.5 mV p to 3.5 V p Unbalanced :off, 0.5 m V p to 1.75 V p				
	White Noise (through ITU-T Rec.G.227 filter)	Level: [Output unit: mV rms, V rms, dBm] At 600 Ω termination when output impedance and output impedance reference set to 600 Ω Balanced: off, -60 dBm (equivalent to 0.774 mV rms) to +6 dBm (equivalent to 1.545 V rms) Unbalanced: off, -60 dBm (equivalent to 0.774 mV rms) to 0 dBm (equivalent to 0.774 V rms)				
	DTMF	Setting: 0 to 9, *, #, A to D (any one) Signal length: 1 to 2000 ms Level: [Output unit: mV p, V p] At 600 Ω termination when output impedance set to 600 Ω Balanced: off, 0.5 mV p to 1.5 V p Unbalanced :off, 0.5 mV p to 0.75 V p				

*1: <Sub Supply/Audio Revision Confirmation Method> (Sub Supply/Audio Revision is the MS2830A-018/118 printed-circuit board version.) (1) MS2830A units with Sub Supply/Audio Revision 2 have a sticker marked 'A1' next to the main-frame serial number.

(2) The MS2830A Sub Supply/Audio Revision can be confirmed as follows:

Press [System Config] \rightarrow [F5] System Information \rightarrow [F4] Board Revision View to list the Board Revisions; check the displayed Sub Supply/Audio Revision number. (It may be either 1 or 2.)

*2: The relationship between the output level units and output level display is explained on the next slide.

<Tx Test> Audio Output Settings (2/2)



<Tx Tests> Audio Analyzer MS2830A-018/118 Settings (Audio Generator Function)

The following settings are supported when the MS2830A-018 (or 118) Audio Analyzer is installed.

Output Type	Balanced, Unbalanced
Output Impedance	Balanced: 100Ω, 600Ω
Output Impedance Reference	Sets the impedance reference used for converting power to dBm.
PTT (Push To Talk)	On/Off setting

Relationship between Output Level Units and Output Level Display From MS2830A firmware Package Version 7.03.00 *1 (all units shipped from March 26, 2015), the relationship between the output units setting and output level display is as follows.

When output units set to dBm	"Termination Power" is displayed. The power consumed by the termination resistance (0 dBm = 1 mW) is displayed. *Up to Package Version 7.02.00, the actual output level was 6 dB lower than the display.
When output units set to mV or V	"Open Circuit Voltage" is displayed.



*1: <Firmware Confirmation Method> Confirm the MS2830A firmware using the following operation.

Press [System Config] \rightarrow [F5] System Information \rightarrow [F2] Software Version View, and check the Package Version displayed at the top right of the screen.

<Tx Test> MX269018A Tx Mode Screen (1/7)



Switch to Tx measurement mode when performing Tx test.

Tx Mode Screen

(With Audio Analyzer installed in MS2830A)



MS2830A-018/118 Audio Analyzer option installed *Explained on following slides



Set AF signal output and confirm radio Tx performance at one screen

<Tx Test> MX269018A Tx Mode Screen (2/7)



Switch to Tx measurement mode when performing Tx test.

Tx Mode Screen

(When Audio Analyzer not installed in MS2830A, or with MS2840A)



<Tx Test> MX269018A Tx Mode Screen (3/7)



Result Window (for FM)

Result Measuring	
(1) RF Frequency 465.037 239 11 MH Freq.Error -0.000 008 89 MHz -0.019110 ppm	z Deviation RMS 1.055 91 kHz Peak+ 1.532 37 kHz (3) (6)
(2) RF Power 29.90 dBm / 977.5 m	(Pk-Pk)/2 1.523 08 kHz
⁽⁴⁾ DCS Code(Normal) 023(340,766,***,	*** , ***) 1.4 0.0 3.0 (5)
 (1): RF Frequency Displays difference between carrier frequency of measured signal and set frequency of Tx Frequency (2): RF Power Displays measurement signal power results in dBm and Watt units when RF Power Set Reference is Off When RF Power Set Reference is set to On, the measured RF Power at that instant becomes the Reference Power and subsequent displayed RF Power results are referenced to that value (3): Deviation Displays +Peak, -Peak, (+Peak to -Peak)/2, RMS results for measured signal frequency deviation in Hz units 	 (4): DCS Code Displays DSC code analysis results with octal notation in three digits when DCS Code Analysis ON The initial code of the displayed result is displayed when the detected code matches the 83 Standard Code defined by TIA-603-C. If there is no match, *** is displayed. Codes in parentheses display code matches other than the 83 Standard Code. (5): Meter displays Displays measured signal Frequency Deviation (+Peak to -Peak)/2 results as meter when modulation setting is FM or Wide FM *Explained on following slides (6): Radian Displayed when Modulation is set to ΦM. Displays the +Peak, -Peak, (+Peak to -Peak)/2, and RMS result of phase transition of measured signal in radian unit. (7): Depth Displayed when Modulation is set to AM. Displays the +Peak, -Peak, (+Peak to -Peak)/2, and RMS result of phase transition of measured signal in radian unit.

<Tx Test> MX269018A Tx Mode Screen (4/7)



AF Measurement Results (TX-AF) Window



(1): AF Frequency

Displays maximum level of frequency from demodulated signal frequency spectrum in Hz units when [AF Frequency Reference] set to [Off]

(2): AF Freq. Error

Displays maximum level of frequency from demodulated signal frequency spectrum relative to reference value when [AF Frequency Reference] set to [On]

(3): Level

Displays level of above-described AF Frequency in kHz rms at FM, radian rms at Φ M, and % at AM

(4): Distortion

Displays distortion measurement results as meter

(5): SINAD

Displays SINAD measurement results as meter

(6): THD

Displays THD measurement results as meter

(7): Measurement results graph

Displays demodulation signal Time vs Level and Frequency vs Level

*Explained on following slides

<Tx Test> MX269018A Tx Mode Screen (5/7)



Audio Generator Window

(1)		(2)	(3)
Audio Generator	Output	Tones DCS Noise I	
 Output 	Tone1 Freq:	1 000.0 Hz Level:	1.00 mVrms 🚺
Common	📨 Tone2 Freq:	67.0 Hz Level:	1.00 mVrms 🛛 🕮
		(4)	

(1): Switches Output/Common

Performs switching between Output and Common. At switching, parameters displayed in (4) change.

Output: Displays parameters for selected waveform

Common: Displays AF signal type, impedance, etc.

(2): Waveform switching

Switches waveform

(3): PTT Status display

Displays PTT (Push To Talk) On/Off

(4): Parameter settings

Sets output AF signal frequency and level

<Tx Test> MX269018A Tx Mode Screen (6/7)



Alphanumeric Magnification Function

Magnification of items displayed on the screen in the Tx mode supports easy reading of text and numeric values. This helps prevent errors when reading numeric values and shortens evaluation times when evaluating wireless equipment operation while watching the screen. In addition, screens can be switched by both button and remote control operation.



<Tx Test> MX269018A Tx Mode Screen (7/7)

Simultaneous AF signal output and spurious/OBW measurements

When the Audio Analyzer MS2830A-018/118 is installed, the audio generator function can be used simultaneously with other applications (spectrum analyzer, signal analyzer, etc.). This can be used to measure the spurious and occupied bandwidth (OBW) of an RF signal output from a radio to which an AF signal (such as white noise) is being input.

The Noise Output function can be used to switch easily between an AF tone (1 kHz, 1.25 kHz) and a white noise signal (ITU-T Recommendation G.227). Pre-registering the output level offset and setting Offset Output to On outputs a signal with the registered signal added (reduced). Use of this function makes it easy to switch the output signal, such as outputting a 1 kHz AF tone first and then outputting a white noise signal (ITU-T Recommendation G.227) . When outputting a white noise signal (ITU-T Recommendation G.227) . When outputting a white noise signal (ITU-T Recommendation G.227) . When outputting a white noise signal (ITU-T Recommendation G.227) . When outputting a white noise signal (ITU-T Recommendation G.227) and the output function to On makes it easy to output a signal with a 10 dB higher level than when outputting the AF tone.





Tx Test

(2): Audio Generator window

This displays a reduced-size Audio Generator window where the output AF signal type, frequency and level can be set.

AF tone (3 waveforms max.), DCS, White noise (ITU-T Recommendation G.227) and DTMF AF signals can be output.

MX269018A Measurement Items & Filter Settings (Rx Test)



<Rx Test> Measurement Items

The following measurement results are displayed when the Audio Analyzer is installed in the MS2830A.

Displayed Item	Outline
AF Measure Result	AF Signal analysis results
AF Frequency	AF Frequency
Level	AF Signal rms level
SINAD, THD, THD+N	AF Signal distortion
Graph Result	AF Signal Time vs Level and Frequency vs Level

<Rx Test> Audio Input Settings

The following settings are supported when the Audio Analyzer is installed in the MS2830A.

	Low Pass Filter	Off, 3, 15, 20, 30, 50 kHz	
Filter	High Pass Filter	Off, 20, 50, 100, 300, 400 Hz, 30 kHz	
	Weighting Filter	Off, CCITT, C-Message, CCIR 468, CCIR-ARM, A-Weighting	
Input Me	thod	Balanced, Unbalanced	
Input Rar	nge	50 mV peak, 500 mV peak, 5 V peak, 50 V peak	
Level Unit		Vrms, dBu, dBV, W, dBm	
Input Impedance Reference		Sets the impedance reference used for converting AF Level	
		measurement value into power of W, dBm.	
Relative Value Display		Input level: Displays value relative to reference value (Using the AF Level measurement result as a 0 dB reference (when this function is set to On), this displays the relative value results of subsequent AF Level measurements.) Input frequency: Displays value relative to reference value	
		(Reference Value: 20 Hz to 60 kHz, Units: ppm, %, Hz)	
Level Display		Displays peak frequency level and level for all bands	

MX269018A Analog Signal Generator Settings (1/2)



<Rx Test> Analog Signal Generator Output Settings

The following settings are supported when the Analog Signal Generator is installed in the MS2830A/MS2840A.

Output Frequency	Frequency setting Range: 100 kHz to 3000 MHz, Frequency setting resolution: 1 Hz
Output Units	dBm, dBµV (EMF), dBµV (Term)
	With output in dBm units:
	–136 to +15 dBm (Rx frequency >25 MHz)
	–136 to –3 dBm (Rx frequency ≤25 MHz)
	With output in dBµV (EMF):
Output Level	-22.99 dBμV to +128.01 dBμV (Rx frequency >25 MHz)
	-22.99 dBµV to +110.01 dBµV (Rx frequency ≤25 MHz)
	With output in dBµV (Term) units:
	–29.01 dBμV to +121.99 dBμV (Rx frequency >25 MHz)
	–29.01 dBµV to +103.99 dBµV (Rx frequency ≤25 MHz)
Output Level Offset	-100.00 to 100.00 dB
Modulation Output	FM, ΦM, AM

MX269018A Analog Signal Generator Settings (2/2)



<Rx Test> Analog Signal Generator Output Settings

The following settings are supported when the Analog Signal Generator is installed in the MS2830A/MS2840A.

Testowers	AF Tone	Simultaneous output of up to 2 or 3* waveforms at any frequency 20.0 to 40000.0 Hz Tone Deviation (FM): 0.0 to 100000.0 Hz Tone Radian (ΦM): 0.00 to 50.00 rad Tone Depth (AM): 0% to 100%
Modulation Signal Source (AF signal)	DCS	At FM modulation output DCS Code: 000 to 777 (octal, 3 digit) DCS Polarity: Normal (polarity not inverted), Inverted (polarity inverted) DCS Deviation: 0.0 to 100000.0 Hz
	USER	At Wave audio file output Frequency: 20.0 to 40000.0 Hz Tone Deviation (FM): 0.0 to 100000.0 Hz Tone Radian (ΦM): 0.00 to 50.00 rad Tone Depth (AM): 0% to 100%

*Outputs up to 3 waveforms when MS2830A-018/118 Audio Analyzer installed

Internal Modulation Signal Source (Analog Signal Generator) (1/2)



The Analog Signal Generator has an internal modulation signal source.

The Analog Signal Generator has up to three internal modulation signal sources for AF tones^{*1}, and one internal signal modulation signal source for DCS. For example, the operation of an analog radio can be confirmed using the following combination.

(1) AF + AF + AF (1 kHz audio signal + Tone squelch signal + voice signal of any frequency)

(2) AF + AF + DCS (1 kHz audio signal + voice signal of any frequency + DCS signal)

(3) AF (Wave audio format)^{*2}

- *1: Two when MS2830A-018/118 Audio Analyzer is not installed
- *2: The internal modulation signal source can be set to output Wave audio format files as well.

An RF signal, such as DTMF (Dual Tone Multiple Frequency), can be output.

The limitations are as follows:

- •Linear PCM file (It is not possible to support ADPCM and the compressed format for enhanced PCM.)
- •Monaural or stereo reproduction (Multi-channel is not supported. The left channel is used to reproduce stereo.)
- •8 or 16-bit sampling quantization rate (full-scale at modulation and modulation depth set)
- •Data replay of 10 s or less
- •44.1 kHz, 48 kHz, or 96 kHz sampling frequency Note: Even if a Wave file meets the above specifications, sometimes the file cannot be loaded.



DCS Code can be set to Binary or Octal Code. Set DCS Code to Octal Code usually, but set to Binary Code for adding errors to DCS Code.

Internal Modulation Signal Source (Analog Signal Generator) (2/2)

Rx Test

The AF signals from the internal modulation source are generated in the following combinations.



Outline of AF Signal Generation Method

- There are three AF signal sources (AF1, AF2, AF3) for generating tone signals* and one signal source for generating the DCS signal.
- The AF3 and DCS signals can be output simultaneously.
- A Wave audio format file can be used instead of a tone signal for AF1. In this case, the AF2 tone, AF3 tone, and DCS (Digital Code Squelch) settings are set to Off automatically.

<Rx Test> MX269018A Rx Mode Screen (1/4)



Switch to Rx measurement mode when performing Rx test.

Rx Mode Screen

(With Analog Signal Generator and Audio Analyzer installed in MS2830A)

(1): Measurement parameters Displays set parameters (2): Audio Analyzer settings window Sets input AF signal analysis conditions (3): AF Measurement results window Displays input AF signal frequency, level, and

Displays input AF signal frequency, level, and distortion as graphs

(4): Function menu

Displays functions executed by function keys

(5): RF Signal Generator window

Displays AF signal settings and output RF signal frequency, level, and modulation settings

*Explained on following slides



The Analog Signal Generator settings and AF signal analysis results can be confirmed on one screen.

<Rx Test> MX269018A Rx Mode Screen (2/4)



Output

Switch to Rx measurement mode when performing Rx test.



nt Unicel: Pre Amp Off

<Rx Test> MX269018A Rx Mode Screen (3/4)



Switch to Rx measurement mode when performing Rx test.

Rx Mode Screen

(With Audio Analyzer installed in MS2830A)





<Rx Test> MX269018A Rx Mode Screen (4/4)



RF Signal Generator Window

		<u></u>		(1)		<u> </u>	(5)
I√ RF Signal Gener	rator	AF1 +A	F2 +AF3 AF1	+AF2 +DCS	User Wave	1	PT
RF Frequency	<i>ı</i> : 465	.037 27	8 MHz Level	: -121.50	dBm	 Output: Modulat 	On tion: O
FM MOD	AF1 Frequ	lency:	1 000.0 Hz	Deviation:	1.500	0 kHz p	0
	AF2 Frequ	lency:	67.0 Hz	Deviation:	0.500	0 kHz p	O
			(3)			
(1): Displays A	AF signal type						
Switches	AF signal type	and highligh	nts selected AF sig	gnal type with pa	rameters in (3)		
(2): Sets RF sig	gnal						
Selects R	F signal setting	j mode					
(3): Sets AF si	gnal						
Selects A	F signal setting	j mode					
(4): Modulation display							
Displays output signal modulation type							
(5): PTT Status display							

Useful Meter Displays

Tx Test Rx Test

Convenient Meter Displays for Rx Sensitivity Tests and Frequency Deviation Measurements

Both numeric tables and convenient meter displays are provided for checking and adjusting Frequency Deviation, SINAD, THD, and Distortion measurements. Using these meters makes it easy to read, intuitively understand, and fine-adjust results for Frequency Deviation (FM) and SINAD at Tx and Rx tests, respectively.



The meters are split into upper and lower parts; setting the upper part narrows the range while the lower part widens the range. The upper part can be used to fine-tune over a narrow range approaching the required value while confirming the wide-ranging variation at the lower meter.



<Tx Test> Audio Signal Graph Displays



Displays Two Types of Graph for Audio Signal Analysis

Two convenient types of graph (Time vs. Level and Frequency vs. Level) are provided for analysis of demodulation signals at Tx tests.



<Rx Test> Audio Signal Graph Displays



Displays Audio Signal Analysis as Two Types of Graph

Two convenient types of graph (Time vs. Level and Frequency vs. Level) are provided for analysis of AF signals <u>at Rx tests using the MS2830A-018/118 Audio Analyzer</u>.

Rx Mode Screen (Displayed when Audio Analyzer installed)



Time axis	Supports scale setting (1 to 200 ms)
Level axis	Only linear scale Auto or fixed range setting <range setting=""></range>
Markers	Convenient markers (Marker 1, Marker 2, Delta marker)

Frequency axis	Supports selection of Log and linear scales <range setting=""> ➤ Log scale: 10 Hz to 50000 Hz ➤ Linear scale: 10 Hz to 50 kHz</range>
Level axis	Only linear scale <range setting=""> ➤ -200 to 50 dBV</range>
Markers	Convenient markers (Marker 1, Marker 2, Delta marker, Peak Search, Next Peak Search)

Demodulated Audio Output

Demodulated Audio Output

The MX269018A Analog Measurement Software supports demodulated audio output. The RF signal from the radio equipment is demodulated and the audio can be monitored.



Option	Demodulation Output Function	Explanation	Supported Modulation Methods	
Analog Measurement Software MX269018A	A0086C USB Audio ^{*1}	Monitor audio using connected USB Audio (requires separately sold speaker or headphone)	FM, ΦM, AM (Wide Band FM measurement not supported)	
	Internal speaker ^{*2}		FM	
Audio Analyzer MS2830A-018/118	Headphone Output connector*2	3.5 mm phone jack (2-pole, monaural)	(Wide Band FM measurement not supported)	
	Demodulation Output connector*2	BNC-J, Impedance: 600Ω, Output: -10 dBm \pm 0.2 dB (frequency deviation = 3.5 kHz)		

*1: Screen display stops during monitoring at USB Audio

Section 3

Specifications

Analog Measurement Software Analog Signal Generator Audio Analyzer

MX269018A Analog Measurement Software Specifications (1/4)

Signal Analyzer		MS2840A	N	/IS2830A		
Tx Measurements		When Input Level proper compared with the input signal is set as long as it doesn't provide separately by each item, the following standards are guaranteed.The Tx measurement specifications apply to the MS2840A, and the MS2830A with built-in MS2830A-062/066 Low Phase Noise Performance Option.No Audio Analyzer optionWithout MS2830A-018/118				
			Audio Analyzer	Audio Analyzer		
Common	Target Signal	FM, WM, AM signal	- 11			
Specification	Frequency Range	100 kHz to the upper limit of the main	UNIT			
	Level Range	-15 to +30 dBm (Preamp Off, or Preamp not installed) -25 to +10 dBm (Preamp On)				
	Carrier Frequency Accuracy	At 18° to 28°C, after calibration ± (Accuracy of reference frequency × Carrier frequency + 1) Hz				
FM Measurement		FM measurement performance under 100 kHz \leq Frequency \leq 2700 MHz (At 10 MHz \leq Frequency \leq 2700 MHz (At	following conditions: FM measurement) Wide Band FM measurement)			
	Frequency Deviation (FM)	0 < Frequency Deviation ≤ 20 kHz 20 kHz < Frequency Deviation ≤ 40 kHz (nominal)				
	Frequency Deviation (Wide Band FM)	0 < Frequency Deviation ≤ 20 kHz 20 kHz < Frequency Deviation ≤ 1 MHz (nominal)				
	Demodulation Frequency Range	20 Hz to 20 kHz				
	Frequency Deviation Accuracy	1% of indicated value \pm Residual FM				
	Residual FM	3.35 Hz rms, S/N: > 50 dB (1.5 kHz Deviation, Demodulation Band: 0.3 kHz to 3 kHz)				
	Demodulation Distortion	0.3% (Demodulation Frequency: 1 kHz, Frequency Deviation: 5 kHz, Demodulation Band: 0.3 kHz to 3 kHz)				
	DCS Measurement Function	Digital Code Squelch demodulated result display				
ФМ Measurement		ΦM measurement performance under 100 kHz \leq Frequency \leq 2700 MHz	following conditions:			
measurement	ΦM Deviation	0 to (20 kHz/Demodulation Frequency	[Hz]) rad			
	Demodulation	20 Hz to 20 kHz				
	Frequency Range					
	ΦM Deviation	1% of indicated value \pm Residual Φ M				
	Accuracy					
	Residual ΦM	0.01 rad rms (Demodulation band: 0.3	kHz to 3 kHz)			
	Demodulation	1% (Demodulation band: 0.3 kHz to 3	kHz)			
	Distortion					
E ANV	Islon onsliro					

MX269018A Analog Measurement Software Specifications (2/4)

urements	When Input Level proper compared wit item, the following standards are guara The Tx measurement specifications app Phase Noise Performance Option. No Audio Analyzer option	h the input signal is set as long as it on teed. Iy to the MS2840A, and the MS2830/	doesn't provide separately by each			
		Without MS2830A-018/118 Audio	With MS2830A-018/118 Audio			
		Analyzer	Analyzer			
	AM measurement performance under f	ollowing conditions:				
A N A	$100 \text{ KHz} \leq \text{Frequency} \leq 2700 \text{ MHz}$					
Demodulation Frequency Range	20 HZ to 20 KHZ					
AM Accuracy	1% of indicated value \pm Residual AM					
Residual AM	0.3% (Demodulation band: 0.3 kHz to 3	0.3% (Demodulation band: 0.3 kHz to 3 kHz)				
Demodulation	0.3% (Demodulation band: 0.3 kHz to 3 kHz)					
Distortion						
LPF	300 Hz, 3, 15, 20 kHz					
HPF	<1*, <20*, 50, 300, 400 Hz, 30 kHz *FM only					
Weighting Filter	CCITT, C-Message, CCIR 468, CCIR-ARM, A-Weighting					
De-emphasis	25 μs, 50 μs, 75 μs, 500 μs, 750 μs,					
Transmit Power	At 18° to 28°C, after calibration, with in	put attenuator ≥10 dB and input sigr	nal in measurement level range and			
Accuracy	less than Input level					
	±0.5 dB (Preamp Off, or Preamp not ins	talled) 2820A main frama Absoluta Amalitus				
Monitor	FM/mM/AM	2830A main frame Absolute Amplitud				
n Output)	Output demodulated signal to USB aud MS2830A/MS2840A USB terminal. (Wide Band FM measurement not supp	lio equipment connected to orted)	Output demodulated signal to USB audio equipment connected to MS2830A USB terminal. (Wide Band FM measurement not supported) FM: Internal speaker, 3.5 mm phone jack or Demodulation Output connector (Wide Band FM			
	AM Demodulation Frequency Range AM Accuracy Residual AM Demodulation Distortion LPF HPF Weighting Filter De-emphasis Transmit Power Accuracy Monitor Output)	AM measurement performance under f 100 kHz \leq Frequency \leq 2700 MHzAM0% to 98%Demodulation20 Hz to 20 kHzFrequency Range20 Hz to 20 kHzAM Accuracy1% of indicated value \pm Residual AMResidual AM0.3% (Demodulation band: 0.3 kHz to 3Demodulation0.3% (Demodulation band: 0.3 kHz to 3Demodulation10,3% (Demodulation band: 0.3 kHz to 3Demodulation25 µs, 50 µs, 75 µs, 500 µs, 750 µs,Transmit PowerAt 18° to 28°C, after calibration, with in less than Input level ± 0.5 dB (Preamp Off, or Preamp not ins Transmit Power Accuracy based on MS: Monitor In Output)MonitorOutputOutputOutput demodulated signal to USB aud MS2830A/MS2840A USB terminal. (Wide Band FM measurement not supp	AM measurement performance under following conditions: 100 kHz ≤ Frequency ≤ 2700 MHz AM 0% to 98% Demodulation 20 Hz to 20 kHz Frequency Range			

MX269018A Analog Measurement Software Specifications (3/4)

	Signal Analyzer	MS2840A	M	S2830A
Rx Power Measurement		This function is enabled e Analog Signal Generator 020/021 Vector Signal Ge Extension for Vector Sign Function Extension for Ve No Audio Analyzer option	either when the MS2830, is installed, or when the enerator and MS2830A/N al Generator and MS283 ector Signal Generator ar without MS2830A- 018/118 Audio Analyzer	A/MS2840A-088 3.6 GHz MS2830A/MS2840A- /S2840A-022 Low Power 0A/MS2840A-029 Analog re installed. with MS2830A-018/118 Audio Analyzer
RF Sign	al Output	The performance specific MS2830A/MS2840A-020,	ations are for the MS283 /021 when the MS2830A	30A/MS2840A-088 /188 or /MS2840A-029 is installed.
	Frequency Setting Range	FM, ΦM, AM : 100 kHz to	3000 MHz	
	Frequency Setting Resolution	1 Hz		
	Output Setting Level	-136 to +15 dBm (RX free -136 to -3 dBm (RX frequ	quency > 25 MHz) iency ≤ 25 MHz)	
FM	Frequency Deviation Setting Range	0 to 100 kHz		
	Frequency Deviation Setting Resolution	0.1 Hz		
	Frequency Deviation Accuracy	$\pm 1\%$ of a setting value (residual FM excluded)		
	Internal Modulation Signal Source	AF Tone Source × 2 Digital Code Squelch Sig	nal Generator	AF Tone Source × 3 Digital Code Squelch Signal Generator
	Internal Modulation Frequency Range	Tone Frequency: 20 Hz to	o 40 kHz	
	Internal Modulation Frequency Resolution	0.1 Hz, Setting value ± 3 Hz on u	use of Digital Code Sque	lch signal
	DCS Code Setting Range	DCS Code: 000 to 777 (or	ctal, 3 digit)	
ΦM Phase Deviation Setting Range Settable with the range of 0 to 50.0 ra phase deviation) < 100 k Hz		of 0 to 50.0 rad (internal ı Hz	modulation frequency \times	
	Phase Deviation Setting Resolution	0.01 rad		
	Phase Deviation Accuracy	$\pm 1\%$ of a setting value (residual ΦM excluded)		
	Internal Modulation Signal Source	AF Tone Source × 2		AF Tone Source × 3
	Internal Modulation Frequency Range	Tone Frequency: 20 Hz to 40 kHz		
	Internal Modulation Frequency Resolution	0.1 Hz		

MX269018A Analog Measurement Software Specifications (4/4)

	Signal Analyzer	MS2840A	MS	2830A
Rx Power Measurement		This function is enabled either when the MS2830A/MS2840A-088 3.6 GHz Analog Signal Generator is installed, or when the MS2830A/MS2840A- 020/021 Vector Signal Generator and MS2830A/MS2840A-022 Low Power Extension for Vector Signal Generator and MS2830A/MS2840A-029 Analog Function Extension for Vector Signal Generator are installed. No Audio Analyzer without MS2830A-		
		option	018/118 Audio Analyzer	Audio Analyzer
AM	Modulation Setting Range	0 to 100%		
	Modulation Setting Resolution	1%		
	Modulation Accuracy	\pm 1% of a setting value (residual AM excluded)		
	Internal Modulation Signal Source	AF Tone Source x 2		AF Tone Source x 3
	Internal Modulation Frequency Range	Tone Frequency: 20 Hz to 40 kHz		
	Internal Modulation Frequency Resolution	0.1 Hz		

MX269018A Analog Signal Generator Specifications (1/1)

Analog Signal Generator Option	MS2840A-029/129/088/188	MS2830A-029/088/188			
Max. reverse input	0 Vdc (max.)				
	+18 dBm (<20 MHz), +30 dBm (≥20 MHz)				
Function/Performance	The following specifications (see MS2840A	The following specifications (see MS2840A The following specifications (see MS2830A			
	brochure) are added to or changed from	brochure) are added to or changed from brochure) are added to or changed from			
	the specifications when the MS2840A-	the specifications when the MS2830A-			
	020/021 and MS2840A-022 are installed	020/021 and MS2830A-022 are installed.			
Frequency Setting Range	FM, ΦM, AM : 100 kHz to 3000 MHz				
Frequency Setting Resolution	1 Hz				
Output Setting Level	-136 to $+15$ dBm (RF frequency > 25 MHz)				
	-136 to -3 dBm (RF frequency ≤ 25 MHz)	-136 to -3 dBm (RF frequency ≤ 25 MHz)			
Output Level Accuracy	with MS2830A-029/088/188, with MS2840A-0	with MS2830A-029/088/188, with MS2840A-029/129/088/188,CW, 18° to 28°C			
		Output level			
		[p](dBm)			
	± 3.0 dB(typ.,100kHz \leq f < 250kHz)	$-110 \le p \le -3$			
	± 1.0 dB(typ.,250kHz $\leq f \leq 25$ MHz)	$-110 \leq p \leq -3$			
	±1.0dB(typ.,25MHz < f < 100MHz)	$-110 \le p \le +4$			
	±0.5dB(typ.,100MHz ≤ f < 375MHz)	$-110 \le p \le +4$			
	± 0.5 dB(375MHz $\leq f \leq 3$ GHz)	$-110 \le p \le +4$			
	± 1.0 dB(100MHz $\leq f \leq 3$ GHz)	$-120 \le p < -110$			
	± 1.0 dB(typ.,100MHz $\leq f \leq 3$ GHz)	-127 ≤ p < -120			
Arbitrary Signal Generator	Available when the MS2830A/MS2840A-020,	021 or 189 (Vector Signal Generator) is			
	installed.	, j			

Audio Analyzer Option Specifications (1/3)

Audio	Analyzer Option	MS2830A-018/118		
Audio A	nalyzer Function	Specifications for single tone measurement		
Connection Ty	pe	Balanced: Standard phone jack (3-pole, Φ6.3 mm)		
		Unbalanced: BNC-J		
Input Impedan	ce	Balanced: 200 kΩ (AC coupled, nominal)		
		Unbalanced: 100 kΩ (AC coupled, nominal)		
Frequency Mea	asurement Range	20 Hz to 50 kHz		
Level Measurer	ment Range	1 mV rms to 25 V rms (30 V rms, max)		
Input Range Se	etting	50 mV peak, 500 mV peak, 5V peak、50V peak		
Level Accuracy		±0.4 dB (20 Hz ≤ f ≤ 25 kHz)		
		±3.0 dB (25 kHz < f ≤50 kHz)		
		(18° to 28°C)		
THD + N		At 1 kHz, 1.4 V rms, 20 Hz to 20 kHz band, 5 Vp-p range, 18° to 28°C:		
(Total Harmoni	ic Distortion + Noise)	<-60 dB		
		<-80 dB (nominal)		
Audio Filter	LPF	Off, 3, 15, 20, 30, 50 kHz		
	HPF	Off, 20, 50, 100, 300, 400 Hz, 30 kHz		
	Weighting Filter	Off, CCITT, C-Message, CCIR468, CCIR-ARM, A-Weighting		

Audio Analyzer Option Specifications (2/3)

Audio Analyzer Option			MS2830A-018/118			
Audio Generator Function			Specifications for all single-tone measurements except White Noise (through ITU-T Rec. G.227 filter)			
Connection Type		E	Balanced: Standard phone jack (3-pole, Φ6.3 mm)			
			Unbalanced: BNC-J			
Interface		I	Balanced: 100 $\Omega/600 \Omega$ (AC coupled, nominal)			
			Unbalanced: 50 $\Omega/600 \Omega$ (AC coupled, nominal)			
Output Waveform			Single tone, multi-tone (Tone × 3, DCS, White Noise (through ITU-T Rec. G.227 filter),			
Guaranteed Freque	ency Range		20 Hz to 25 kHz			
Frequency Setting	Range		10 Hz to 50 kHz			
Frequency Resoluti	on	(0.01 Hz			
Output Level	Using Sub Supply	/Audio Revis	sion 2 *2 (all units shipped from March 26, 2015)			
Range *1	5 11 5					
	Single tone					
	Open circuit voltage	Balanced	off, 1 mV rms to 12.4 V rms			
	(≥ 100 k Ω Termination)	Unbalanced	off, 1 mV rms to 6.2 V rms			
	600 Ω Termination ^{*2}	Balanced	off, -63 dBm (equivalent to 0.5 mV rms) to +18 dBm (equivalent to 6.2 V rms)			
		Unbalanced	off, -63 dBm (equivalent to 0.5m V rms) to +12 dBm (equivalent to 3.1 V rms)			
	White Noise (thr	ough ITU-T (G.227 filter)			
	Open circuit voltage ($\geq 100 \text{ k}\Omega$ Termination)	Balanced	off, 1.545 mV rms to 3.083 V rms (nominal)			
		Unbalanced	off, 1.545 mV rms to 1.545 V rms (nominal)			
	600 0	Balanced	off, -60 dBm (equivalent to 0.774 mV rms) to +6 dBm (equivalent to 1.545 V rms) (nominal)			
	Termination ^{*2}	Unbalanced	off, –60 dBm (equivalent to 0.774 mV rms) to 0 dBm (equivalent to 0.774 V rms) (nominal)			

*1: Output Impedance = 600 Ω , and Output Impedance Reference = 600 Ω

Refer to the 'Interface Setting Example (Audio Analyzer)' slides for the voltage and power calculations.

Audio Analyzer Option Specifications (3/3)

Audio A	Analyzer Option	MS2830A-018/118		
Audio Gen	erator Function	Standard for all single-tone measurements except White Noise (through ITU-T Rec. G.227 filter)		
Output Level Resolution		Single Tone: 1 mV (350 mV rms < Output Level ≤ 6.2 V rms) 100 μV (35 mV rms < Output Level ≤ 350 mV rms)		
		10 μV (Output Level ≤ 35 mV rms) White Noise (through ITU-T Rec. G.227 filter): 0.01dB		
Level Accuracy		Single Tone ±0.3 dB (1 kHz, 100 kΩ termination, 18° to 28°C) White Noise (through ITU-T Rec. G.227 filter): ±3 dB (nominal)		
Maximum Outpu	It Currency	100 mA (nominal, no short circuit)		
THD + N		At 1 kHz, 0.7 Vrms, 20 Hz to 25 kHz band, $100k\Omega$ termination, 18° to 28° C:		
(Total Harmonic Distortion + Noise)		<-60 dB <-80 dB (nominal)		
Weighting Filter	(White Noise)	ITU-T Recommendation G.227		
Other Fur	nction			
Demodulation	Demodulation Output Level	$-10 \text{ dBm} \pm 2 \text{ dB}$ (Frequency Deviation = 3.5 kHz, 600 Ω)		
Output (FM only)	Demodulation Output Impedance	600 Ω		
	Sound Monitor	Internal speaker or 3.5 mm phone jack (2-pole, monaural)		
Crosstalk		Crosstalk from Audio Generator to Audio Analyzer >80 dB		
PTT (Push To Talk) Control		Вапапа jack (Ф4.0 mm, 30 V max, 500 mA max.)		
General Input/Output (Audio Function)		Connector: D-Sub 15pin (jack) Function: Open Collector \times 1(5 V, 100 mA max.), TTL Output: \times 2, TTL Input \times 2		

*2: Sub Supply/Audio Revision is the MS2830A-018/118 printed-circuit board version.

<Sub Supply/Audio Revision Confirmation Method>

(1) MS2830A units with Sub Supply/Audio Revision 2 have a sticker marked 'A1' next to the main-frame serial number.

(2) The MS2830A Sub Supply/Audio Revision can be confirmed as follows:

Press [System Config] \rightarrow [F5] System Information \rightarrow [F4] Board Revision View to list the Board Revisions; check the displayed Sub Supply/Audio Revision number. (It may be either 1 or 2.)

Section 4



MS2830A Ordering Information (1/2)

	Name	Model		Note	
		New	Retrofit*3	1	
Mandatory	3.6 GHz Signal Analyzer	MS2830A-040	-	9 kHz to 3.6 GHz, Cannot retrofit.	
	6 GHz Signal Analyzer	MS2830A-041	-	9 kHz to 6 GHz, Cannot retrofit.	
	13.5 GHz Signal Analyzer	MS2830A-043	-	9 kHz to 13.5 GHz, Cannot retrofit.	
				Cannot be installed MS2830A-066 and signal	
				generator options simultaneously	
Mandatory	Low Phase Noise Performance	MS2830A-066	-	Improved phase noise performance	
				Cannot retrofit.	
Mandatory	Analog Measurement Software	MX26	59018A*1	Frequency setting range:	
				At FM/ФM/AM measurement : 100 kHz to the upper	
				limit of the main unit	
				At Wide Band FM measurement: 10 MHz to the	
				upper limit of the main unit	
Mandatory	USB Audio	A0	086C	Necessary for demodulated sound output	
Recommend	High Stability Reference Oscillator	MS2830A-002	MS2830A-102	Aging Rate: $\pm 1 \times 10^{-7}$ /year	
				Start-up Characteristics: \pm 5 x 10 ⁻⁸ (5 minutes after	
				power-on)	
	3.6GHz Analog Signal Generator	MS2830A-088	MS2830A-188*1	Frequency setting range (FM, ΦM, AM): 100 kHz to 3	
				GHz, Cannot be installed with MS2830A-043.	
				(Require MX269018A, A0086C)	
	Audio Analyzer	MS2830A-018	MS2830A-118*1		
	Vector Function Extension for	-	MS2830A-189	Add vector function to MS2830A-088/188	
	Analog Signal Generator				
	3.6 GHz Vector Signal Generator	MS2830A-020	MS2830A-120	250 kHz to 3.6 GHz	
	6 GHz Vector Signal Generator	MS2830A-021	MS2830A-121	250 kHz to 6 GHz	
	Low Power Extension for Vector	MS2830A-022	MS2830A-122	Extends lower output level limit.	
	Signal Generator			Mandatory to MS2830A-029	
	Analog Function Extension for	MS2830A-029	↓ ↓ 2	Add analog function to MS2830A-020/120/021/121	
	Vector Signal Generator	al Generator		(Require MS2840A-022/122, MX269018A, A0086C)	
	Internal Signal Generator Control	MS2830A-052	MS2830A-152	Functions equivalent to tracking generator	
	Function				

*1: MS2830A-188/118 Retrofit conditions

✓ Requires previous installation of either MS2830A-066 or MS2830A-062 in MS2830A main frame

✓ Requires MX269018A and A0086C sold separately

✓ MS2830A-188 cannot be retrofitted to 13.5 GHz model (MS2830A-043)

*2: Please contact our sales representative when requiring the MS2830A-029 retrofit.

*3: Installation Kit Z1345A is required.

Anritsu envision : ensure

MS2830A Ordering Information (2/2)

Optional combination necessary for mounting analog signal generator

Option model are decided by the MS2830A which required analog signal generator (SG). Please note that there is a case where an analog SG function cannot be installed for a part of MS2830A composition.

MS2830A installed analog SG		New MS2830A	The case that retrofit analog SG to M		VIS2830A
Frequency option of MS2830A		MS2830A ↓ (3.6GHz/6G with MS2830/		A-040/041 GHz models A-066 or 062)	MS2830A-043 (13.5GHz model)
Installe	d vector SG	\checkmark	Not installed MS2830A-020/021		\checkmark
SG	Analog SG	MS2830A-088 + MS2830A-066 + MX269018A + A0086C	MS2830A-188 + MX269018A*3 + A0086C*3 + Z1345A	*1	
& mandatory option that can be added	Analog SG + Vector SG	MS2830A-020/021 + MS2830A-022 + MS2830A-029 + MS2830A-066 + MX269018A + A0086C	MS2830A-188 ^{*2} + MS2830A-189 ^{*2} + MX269018A ^{*3} + A0086C ^{*3} + Z1345A	_	Cannot be installed

*1: Please contact our sales representative.

*2: Can select only 3.6 GHz Vector SG/Analog SG

*3: Unnecessary MX269018A and A0086C already installed

With 3.6 GHz Signal Analyzer (MS2840A-040) or 6 GHz Signal Analyzer (MS2840A-041)

	Name	Model		Note	
		New	Retrofit *1		
Mandatory	3.6 GHz Signal Analyzer	MS2840A-040	-	9 kHz to 3.6 GHz, Cannot retrofit.	
	6 GHz Signal Analyzer	MS2840A-041	-	9 kHz to 6 GHz, Cannot retrofit.	
Mandatory	Analog Measurement Software	MX269018A		Frequency setting range: At FM/ΦM/AM measurement: 100 kHz to the upper limit of the main unit At Wide Band FM measurement: 10 MHz to the upper limit of the main unit	
Mandatory	USB Audio	A0086C		Necessary for demodulated sound output	
Recommend	Low Phase Noise Performance	MS2840A-066	MS2840A-166	Improves phase noise performance. This option greatly improves SSB phase noise performance.	
	High Stability Reference Oscillator	MS2840A-002	MS2840A-102	Aging Rate: $\pm 1 \times 10^{-7}$ /year Start-up Characteristics: $\pm 5 \times 10^{-8}$ (5 minutes after power-on)	
	3.6GHz Analog Signal Generator	MS2840A-088 MS2840A-188		Frequency setting range (FM, ΦM, AM): 100 kHz to 3 GHz (Require MX269018A, A0086C)	
	Vector Function Extension for Analog Signal Generator	-	MS2840A-189	Add vector function to MS2840A-088/188	
	3.6 GHz Vector Signal Generator	MS2840A-020	MS2840A-120	250 kHz to 3.6 GHz	
	6 GHz Vector Signal Generator	MS2840A-021	MS2840A-121	250 kHz to 6 GHz	
	Low Power Extension for Vector Signal Generator	MS2840A-022	MS2840A-122	Extends lower output level limit Mandatory for MS2840A-029/129	
	Analog Function Extension for Vector Signal Generator	MS2840A-029	MS2840A-129	Add analog function to MS2840A-020/120/021/121 (Require MS2840A-022/122, MX269018A, A0086C)	

*1: Require Installation Kit Z1932A

With 26.5 GHz Signal Analyzer (MS2840A-044) or 44.5 GHz Signal Analyzer (MS2840A-046)

	Name	Model		Note
		New	Retrofit *1	
Mandatory	26.5 GHz Signal Analyzer	MS2840A-044	-	9 kHz to 26.5 GHz, Cannot retrofit.
	44.5 GHz Signal Analyzer	MS2840A-046	-	9 kHz to 44.5 GHz, Cannot retrofit.
Mandatory	Analog Measurement Software	MX269018A		Frequency setting range: At FM/ФM/AM measurement: 100 kHz to the upper limit of the main unit At Wide Band FM measurement: 10 MHz to the upper limit of the main unit
Mandatory	USB Audio	A00	86C	Necessary for demodulated sound output

*1: Require Installation Kit Z1932A

Optional combination necessary for mounting analog signal generator

Option model are decided by the MS2840A which required analog signal generator (SG). Please note that there is a case where an analog SG function cannot be installed for a part of MS2840A composition.

MS2840A installed ar	nalog SG	New MS2840A	The case that retrofit analog SG to MS2840A	
Frequency option of N	/IS2840A	\rightarrow	MS2840A-040/041 (3.6GHz/6GHz model)	
Installed vector	SG	\rightarrow	Not installed	MS2840A-020/021
SG &	Analog SG	MS2840A-088 + MX269018A + A0086C	MS2830A-188 + MX269018A*2 + A0086C*2 + Z1932A	MS2840A-129 + MS2840A-122 ^{*2} + MX269018A ^{*2} + A0086C ^{*2} + Z1932A
Mandatory options that can be added	Analog SG + Vector SG	MS2840A-020/021 + MS2840A-022 + MS2840A-029 + MX269018A + A0086C	MS2840A-188 ^{*1} + MS2840A-189 ^{*1} + MX269018A ^{*2} + A0086C ^{*2} + Z1932A	_

*1: Can select only 3.6 GHz Vector SG/Analog SG

*2: Unnecessary when MS2840A-022, MX269018A and A0086C already installed

Option Addition MS2830A

Adding the Internal Signal Generator Control Function MS2830A-052 to the MS2830A with installed Analog Signal Generator supports the spectrum analyzer (SPA) and signal generator (SG) tracking function for measuring transmission characteristics of filters, amplifiers, etc.



Measure Both Passive and Active Devices

The DUT input signal source has a frequency range of 100 kHz to 3.6 GHz or 6 GHz*, an output level range of -136 dBm to +15 dBm, a step resolution of 0.01 dB, and a level accuracy of ±0.5 dB to measure both passive and active devices using the built-in high-performance SG.

✓ Accurate Frequency Characteristics

The SPA function displays the measured frequency characteristics results with an excellent linearity error of just ±0.07 dB to display the frequency characteristics of band-pass filters, etc., accurately.

*Changes according to option for SG

Application parts

USB Power Sensor

Power measurement is available with USB Power Sensor connected to MS2830A and MS2840A.

Model	Name	Note
MA24105A	Inline Peak Power Sensor	Corresponding to the measurement of continuous wave Frequency: 350 MHz to 4 GHz, Dynamic Range: +3 to +51.76 dBm
MA24106A	USB Power Sensor	Corresponding to the measurement of continuous wave Frequency: 50 MHz to 6 GHz, Dynamic Range: -40 to +23 dBm
MA24108A	Microwave USB Power Sensor	Corresponding to the measurement of continuous wave and burst wave Frequency: 10 MHz to 8 GHz, Dynamic Range: -40 to +20 dBm
MA24118A	Microwave USB Power Sensor	Corresponding to the measurement of continuous wave and burst wave Frequency: 10 MHz to 18 GHz, Dynamic Range: -40 to +20 dBm
MA24126A	Microwave USB Power Sensor	Corresponding to the measurement of continuous wave and burst wave Frequency: 10 MHz to 26 GHz, Dynamic Range: -40 to +20 dBm



[Power meter application main screen]







