

Technical Data Sheet

TOSLN50A-8 Calibration Kit

Type N(m)
DC to 8 GHz, 50 Ω



This calibration kit has been designed to provide superior measurement results when used with precision instruments. It is designed for use in both field and lab environments. It is a high precision component and should be handled with proper care. Excessive shock, torque, or power should be avoided to prevent permanent damage.

Specifications for units within recommended calibration cycle are guaranteed under the following conditions:

1. Unit is operated within specified temperature range.
2. Unit has not been subjected to damage from mishandling.

Length, capacitance, and inductance are nominal values.

Open and Short Phase, Through Return Loss and Insertion Loss, and DC Resistance specifications are typical. Phase is measured as a deviation from the model defined by offset length and inductance or capacitance.

Operating Temperature Range	-10 °C to +55 °C (MIL-PRF-28800F, Class 2)
Storage Temperature Range	-51 °C to +71 °C (MIL-PRF-28800F, Class 2)
Recommended Calibration Interval	1 year

For the latest information, sales, or service, visit: www.anritsu.com

TOSLN50A-8 Calibration Kit TDS
Copyright June 2017 Anritsu Company, USA
All Rights Reserved



11410-00737



C

© Anritsu All trademarks are registered trademarks of their respective companies. Data subject to change without notice. Anritsu prints on recycled paper with vegetable soybean oil ink.



TOSLN50A-8 Calibration Kit Specifications

Through (Thru)	Spec
Length	58.5 mm
Return Loss (DC to 6 GHz)	≥ 40 dB
Return Loss (6 to 8 GHz)	≥ 36 dB
Insertion Loss (DC to 8 GHz)	≤ 0.025 x √(f/GHz) dB

Open	Spec
Length	17.83 mm
C0 (1E-15) F	4.000
C1 (1E-27) F/Hz	200.000
C2 (1E-36) F/Hz ²	0.000
C3 (1E-45) F/Hz ³	1.100
Phase (DC to 6 GHz)	≤ ± 2.0°
Phase (6 to 8 GHz)	≤ ± 3.0°

Short	Spec
Length	17.83 mm
L0 (1E-12) H	0.000
L1 (1E-24) H/Hz	0.000
L2 (1E-33) H/Hz ²	0.000
L3 (1E-42) H/Hz ³	0.000
Phase (DC to 6 GHz)	≤ ± 1.5°
Phase (6 to 8 GHz)	≤ ± 2.5°

Load	Spec
DC Resistance	50 Ω ± 0.25 Ω
Return Loss (DC to 6 GHz)	≥ 42 dB
Return Loss (6 to 8 GHz)	≥ 37 dB
Max Power	1.0 W