

Technical Data Sheet

TOSLN50A-18 Calibration Kit

Type N(m)
DC to 18 GHz, 50 Ω



This calibration kit has been designed to provide superior measurement results when used with precision instruments. It is designed for use in both field and lab environments. It is a high precision component and should be handled with proper care. Excessive shock, torque, or power should be avoided to prevent permanent damage.

Specifications for units within recommended calibration cycle are guaranteed under the following conditions:

1. Unit is operated within specified temperature range.
2. Unit has not been subjected to damage from mishandling.

Length, capacitance, and inductance are nominal values.

Open and Short Phase, Through Return Loss and Insertion Loss, and DC Resistance specifications are typical. Phase is measured as a deviation from the model defined by offset length and inductance or capacitance.

| | |
|---|--|
| Operating Temperature Range | -10 °C to +55 °C (MIL-PRF-28800F, Class 2) |
| Storage Temperature Range | -51 °C to +71 °C (MIL-PRF-28800F, Class 2) |
| Recommended Calibration Interval | 1 year |

Calibration Options

- TOSLN-0098 Standard Calibration to ISO17025 and ANSI/NCSL Z540-1. Includes calibration certificate.
- TOSLN-0099 Premium Calibration to ISO17025 and ANSI/NCSL Z540-1. Includes calibration certificate, test report, and uncertainty data.

For the latest information, sales, or service, visit: www.anritsu.com

TOSLN50A-18 Calibration Kit TDS
Copyright December 2020 Anritsu Company, USA
All Rights Reserved

© Anritsu All trademarks are registered trademarks of their respective companies. Data subject to change without notice. Anritsu prints on recycled paper with vegetable soybean oil ink.



11410-00738



D

TOSLN50A-18 Calibration Kit Specifications

| Through (Thru) | Spec |
|----------------------------|------------------------------------|
| Length | 58.5 mm |
| Return Loss (DC to 6 GHz) | ≥ 40 dB |
| Return Loss (6 to 9 GHz) | ≥ 36 dB |
| Return Loss (9 to 18 GHz) | ≥ 32 dB |
| Insert Loss (DC to 18 GHz) | ≤ 0.025 x $\sqrt{f/\text{GHz}}$ dB |

| Open | Spec |
|------------------------------|----------|
| Length | 17.83 mm |
| C0 (1E-15) F | 4.000 |
| C1 (1E-27) F/Hz | 200.000 |
| C2 (1E-36) F/Hz ² | 0.000 |
| C3 (1E-45) F/Hz ³ | 1.100 |
| Phase (DC to 6 GHz) | ≤ ± 2.0° |
| Phase (6 to 9 GHz) | ≤ ± 3.0° |
| Phase (9 to 18 GHz) | ≤ ± 4.0° |

| Short | Spec |
|------------------------------|----------|
| Length | 17.83 mm |
| L0 (1E-12) H | 0.000 |
| L1 (1E-24) H/Hz | 0.000 |
| L2 (1E-33) H/Hz ² | 0.000 |
| L3 (1E-42) H/Hz ³ | 0.000 |
| Phase (DC to 6 GHz) | ≤ ± 1.5° |
| Phase (6 to 9 GHz) | ≤ ± 2.5° |
| Phase (9 to 18 GHz) | ≤ ± 3.0° |

| Load | Spec |
|---------------------------|---------------|
| DC Resistance | 50 Ω ± 0.25 Ω |
| Return Loss (DC to 6 GHz) | ≥ 42 dB |
| Return Loss (6 to 9 GHz) | ≥ 37 dB |
| Return Loss (9 to 18 GHz) | ≥ 33 dB |
| Max Power | 1.0 W |